

**APPARATUS TO DETECT AND TREAT ABERRANT
MYOELECTRIC ACTIVITY**

Inventor: Stuart D. Edwards

BACKGROUND OF THE INVENTION

5 **Cross-Related Applications**

10 This application is a continuation-in-part of U.S. Patent Application
Serial No. 08/731,372, filed October 11, 1996, which is a continuation-in-
part of U.S. Patent Application Serial No. 08/319,373, filed October 6,
1994, which is a continuation-in-part of U.S. Application No. 08/286,862,
filed August 4, 1994, which is a continuation-in-part of U.S. Patent
Application Serial No. 08/272,162, filed July 7, 1994, which is a
continuation-in-part of U.S. Patent Application Serial No. 08/265,459, filed
June 24, 1994, and is related to concurrently filed Application entitled
"GERD Treatment Apparatus and Method" identified as Attorney Docket
15 14800-748, all with named inventor Stuart D. Edwards, and all of which are
incorporated herein by reference.

Field of the Invention

20 This invention relates generally to an apparatus to detect and treat
aberrant myoelectric activity, and more particularly the detection and
treatment in a sphincter and/or stomach.

Description of Related Art

Gastroesophageal reflux disease (GERD) is a common
gastroesophageal disorder in which the stomach contents are ejected into the

lower esophagus due to a dysfunction of the lower esophageal sphincter (LES). These contents are highly acidic and potentially injurious to the esophagus resulting in a number of possible complications of varying medical severity. The reported incidence of GERD in the U.S. is as high as 10% of the population (Castell DO; Johnston BT: *Gastroesophageal Reflux Disease: Current Strategies For Patient Management*. Arch Fam Med, 5(4):221-7; (1996 April)).

Acute symptoms of GERD include heartburn, pulmonary disorders and chest pain. On a chronic basis, GERD subjects the esophagus to ulcer formation, or esophagitis and may result in more severe complications including esophageal obstruction, significant blood loss and perforation of the esophagus. Severe esophageal ulcerations occur in 20-30% of patients over age 65. Moreover, GERD causes adenocarcinoma, or cancer of the esophagus, which is increasing in incidence faster than any other cancer (Reynolds JC: *Influence Of Pathophysiology, Severity, And Cost On The Medical Management Of Gastroesophageal Reflux Disease*. Am J Health Syst Pharm, 53(22 Suppl 3):S5-12 (1996 Nov 15)).

One of the possible causes of GERD may be aberrant electrical signals in the LES or the stomach. Such signals may cause a higher than normal frequency of relaxations of the LES allowing acidic stomach contents to be repeatedly ejected into the esophagus and cause the complications described above. Research has shown that unnatural electrical signals in the stomach and intestine can cause reflux events in those organs (Kelly KA, et al: *Duodenal-gastric Reflux and Slowed Gastric Emptying by Electrical Pacing of the Canine Duodenal Pacemaker Potential*. Gastroenterology. 1977 Mar; 72(3): 429-433). In particular, medical research has found that sites of aberrant electrical activity or electrical foci may be responsible for

those signals (Karlstrom LH, et al.: *Ectopic Jejunal Pacemakers and Enterogastric Reflux after Roux Gastrectomy: Effect Intestinal Pacing Surgery*. 1989 Sep; 106(3): 486-495). Similar aberrant electrical sites in the heart, which cause contractions of the heart muscle to take on life threatening patterns or dysrhythmias, can be identified and treated using mapping and ablation devices as described in U.S. Patent No. 5,509,419. However, there is no current device or associated medical procedure available for the electrical mapping and treatment of aberrant electrical sites in the LES and stomach as a means for treating GERD.

Current drug therapy for GERD includes histamine receptor blockers which reduce stomach acid secretion and other drugs which may completely block stomach acid. However, while pharmacologic agents may provide short term relief, they do not address the underlying cause of LES dysfunction.

Invasive procedures requiring percutaneous introduction of instrumentation into the abdomen exist for the surgical correction of GERD. One such procedure, Nissen fundoplication, involves constructing a new "valve" to support the LES by wrapping the gastric fundus around the lower esophagus. Although the operation has a high rate of success, it is an open abdominal procedure with the usual risks of abdominal surgery including: postoperative infection, herniation at the operative site, internal hemorrhage and perforation of the esophagus or of the cardia. In fact, a recent 10 year, 344 patient study reported the morbidity rate for this procedure to be 17% and mortality 1% (Urschel, JD: *Complications Of Antireflux Surgery*, Am J Surg 166(1): 68-70; (1993 July)). This rate of complication drives up both the medical cost and convalescence period for the procedure and may

exclude portions of certain patient populations (e.g., the elderly and immuno-compromised).

Efforts to perform Nissen fundoplication by less invasive techniques have resulted in the development of laparoscopic Nissen fundoplication. Laparoscopic Nissen fundoplication, reported by Dallemagne et al. *Surgical Laparoscopy and Endoscopy*, Vol. 1, No. 3, (1991), pp. 138-43 and by Hindler et al. *Surgical Laparoscopy and Endoscopy*, Vol. 2, No. 3, (1992), pp. 265-272, involves essentially the same steps as Nissen fundoplication with the exception that surgical manipulation is performed through a plurality of surgical cannula introduced using trocars inserted at various positions in the abdomen.

Another attempt to perform fundoplication by a less invasive technique is reported in U.S. Patent No. 5,088,979. In this procedure an invagination device containing a plurality of needles is inserted transorally into the esophagus with the needles in a retracted position. The needles are extended to engage the esophagus and fold the attached esophagus beyond the gastroesophageal junction. A remotely operated stapling device, introduced percutaneously through an operating channel in the stomach wall, is actuated to fasten the invaginated gastroesophageal junction to the surrounding involuted stomach wall.

Yet another attempt to perform fundoplication by a less invasive technique is reported in US Patent No. 5,676,674. In this procedure, invagination is done by a jaw-like device and fastening of the invaginated gastroesophageal junction to the fundus of the stomach is done via a transoral approach using a remotely operated fastening device, eliminating the need for an abdominal incision. However, this procedure is still traumatic to the LES and presents the postoperative risks of gastroesophageal leaks, infection and foreign body reaction, the latter two

seuela resulting when foreign materials such as surgical staples are implanted in the body.

While the methods reported above are less invasive than an open Nissen fundoplication, some still involve making an incision into the abdomen and hence the increased morbidity and mortality risks and convalescence period associated with abdominal surgery. Others incur the increased risk of infection associated with placing foreign materials into the body. All involve trauma to the LES and the risk of leaks developing at the newly created gastroesophageal junction. None provide a means for detecting and treating aberrant electrical sites causing abnormal LES relaxation and gastroesophageal reflux.

There is a need to provide an apparatus to detect and treat aberrant myoelectric activity of a sphincter and/or a stomach. There is another need to provide an apparatus to detect and treat an electrical foci of the aberrant myoelectric activity of a sphincter and/or a stomach. There is a further need to detect and treat an electrically conductive pathway of the aberrant myoelectric activity of a sphincter and/or a stomach.

SUMMARY OF THE INVENTION

Accordingly, an object of the invention is to provide an apparatus to diagnose and treat sphincters and/or a stomach.

5 Another object of the invention is to provide an apparatus to diagnose and treat GERD.

A further object of the invention is to provide an apparatus to detect and treat aberrant myoelectric activity of a sphincter and/or a stomach.

10 Yet another object of the invention is to provide an apparatus to detect and treat an electrical foci of aberrant myoelectric activity of a sphincter and/or a stomach.

Still a further object of the invention is to provide an apparatus to detect and treat an electrically conductive pathway of aberrant myoelectric activity of a sphincter and/or a stomach.

15 Another object of the invention is to provide an apparatus to detect and treat an electrical foci of aberrant myoelectric activity of a lower esophageal sphincter and/or a stomach.

A further object of the invention is to provide an apparatus to detect and treat an electrically conductive pathway of aberrant myoelectric activity of a lower esophageal sphincter and/or a stomach.

20 These and other objects of the invention are provided in an apparatus to treat a sphincter that has a support member. A sphincter electropotential mapping device includes a mapping electrode. The sphincter electropotential mapping device is coupled to the support member and configured to detect one of an aberrant neuroelectric or myoelectric activity of the sphincter or
25 stomach.

In another embodiment, an apparatus to treat a stomach has a support member. A stomach electropotential mapping device includes a

mapping electrode. The stomach electropotential mapping device is coupled to the support member and configured to detect and treat one of an aberrant neuroelectric or myoelectric activity of the stomach.

5 Additionally, the electropotential mapping device can also include one or more treatment electrodes.

BRIEF DESCRIPTION OF THE DRAWINGS

10 FIG. 1 is an illustrated lateral view of the upper GI tract including the esophagus and lower esophageal sphincter and the positioning of the sphincter mapping and treatment apparatus of the present invention in the lower esophageal sphincter.

15 FIG. 2 is a lateral view of the present invention illustrating the energy delivery device, power source, controllers, map, display device, and the mapping assembly in an expanded and contracted state.

FIG. 3 depicts a lateral view of the present invention that illustrates components on the flexible shaft including a proximal fitting, connections and proximal and distal shaft segments.

FIG. 4A illustrates a lateral view of the basket assembly used in an embodiment of the invention.

20 FIG. 4B is a lateral view that illustrates placement of the mapping electrodes on the basket assembly and their electrical connections to the controller.

FIG. 5A is a lateral view of the basket assembly that illustrates the range of camber in the basket assembly.

25 FIG. 5B is a perspective view illustrating a balloon coupled to the basket assembly.

FIG. 6A is a lateral view of the junction between the basket arms and the shaft illustrating the pathway used for advancement of the movable wire or the delivery of fluids.

FIG. 6B is a frontal view of a basket arm in an alternative embodiment of the invention illustrating a track in the arm used to advance the movable wire.

FIG. 7 is a cross-sectional view of a section of the basket arm illustrating stepped and tapered sections in basket arm apertures.

FIG. 8 is a lateral view of the basket assembly illustrating the placement of the radial supporting member.

FIG. 9A is a lateral view of the sphincter mapping and treatment apparatus illustrating the mechanism used in one embodiment of the invention to increase the camber of the basket assembly.

FIG. 9B is a similar view to 9A showing the basket assembly in an increased state of camber.

FIG. 10 is a lateral view of the sphincter mapping and treatment apparatus illustrating the deflection mechanism.

FIG. 11 is a lateral view illustrating the use of electrolytic solution to create an enhanced RF electrode.

FIG. 12 is a lateral view of the basket assembly illustrating the use of needle electrodes.

FIG. 13 is a lateral view illustrating the use of an insulation segment on the needle electrode to protect an area of tissue from RF energy.

FIG. 14 is a lateral view illustrating the placement of needle electrodes into the sphincter wall by expansion of the basket assembly.

FIG. 15 is a lateral view illustrating placement of needle electrodes into the sphincter wall by advancement of an electrode delivery member out of apertures in the basket arms.

FIG. 16 is a cross sectional view illustrating the configuration of a basket arm aperture used to select and maintain a penetration angle of the needle electrode into the sphincter wall.

FIG. 17 is a lateral view illustrating placement of needle electrodes into the sphincter wall by advancement of an electrode delivery member directly out of the distal end of the shaft.

FIG. 18A is a lateral view illustrating a radial distribution of electrodes on the expandable mapping assembly of the invention.

FIG. 18B is a lateral view illustrating a longitudinal distribution of electrodes on the expandable mapping assembly of the invention.

FIG. 18C is a lateral view illustrating a spiral distribution of electrodes on the expandable mapping assembly of the invention.

FIG. 18D is a lateral view illustrating a radial-longitudinal distribution of electrodes on the expandable mapping assembly of the invention.

FIG. 19 is a flow chart illustrating a sphincter treatment method.

FIG. 20 is a lateral view of sphincter smooth muscle tissue illustrating electromagnetic foci and pathways for the origination and conduction of aberrant electrical signals in the smooth muscle of the lower esophageal sphincter or other tissue.

FIG. 21 is a lateral view of a sphincter wall illustrating the infiltration of tissue healing cells into a lesion in the smooth tissue of a sphincter following treatment with the sphincter treatment apparatus of the present invention.

FIG. 22 is a view similar to that of FIG. 21 illustrating shrinkage of the lesion site caused by cell infiltration.

FIG. 23 is a lateral view of the esophageal wall illustrating the preferred placement of lesions in the smooth muscle layer of a esophageal sphincter.

FIG. 24 is a lateral view illustrating the ultrasound transducer, ultrasound lens and power source of an embodiment of the present invention.

FIGS. 25A-D are lateral views of the sphincter wall illustrating various patterns of lesions created by the apparatus of the present invention.

FIG. 26 is a lateral view of the sphincter wall illustrating the delivery of cooling fluid to the electrode-tissue interface and the creation of cooling zones.

FIG. 27 depicts the flow path, fluid connections and control unit employed to deliver fluid to the electrode-tissue interface.

FIG. 28 depicts the flow path, fluid connections and control unit employed to deliver fluid to the RF electrodes.

FIG. 29 is an enlarged lateral view illustrating the placement of sensors on the expansion device or basket assembly.

FIG. 30 depicts a block diagram of the feed back control system that can be used with the sphincter mapping and treatment apparatus.

FIG. 31 depicts a block diagram of an analog amplifier, analog multiplexer and microprocessor used with the feedback control system of FIG. 30.

FIG. 32 depicts a block diagram of the operations performed in the feedback control system depicted in FIG. 30.

DETAILED DESCRIPTION

Referring now to FIGS. 1 and 2, one embodiment of sphincter mapping and treatment apparatus 10 that is used to map the myoelectric activity of and deliver energy to a treatment site 12 to produce lesions 14 in a sphincter 16, such as the lower esophageal sphincter (LES), comprises a flexible elongate shaft 18, also called shaft 18, coupled to an expandable mapping assembly 20, in turn coupled with one or more mapping electrodes 22.

Expandable mapping assembly 20 establishes a three dimensional array of mapping electrodes 22. In use, the expandable mapping assembly 20 records the activation times, the distribution, and the waveforms of the myoelectrical and neuroelectrical action potentials in sphincter 16, which can include the LES, and adjoining structures that trigger aberrant relaxation of muscle tissue in sphincter 16. Suitable materials for mapping electrodes 22 include gold, platinum and other metals known to those skilled in the art.

Mapping electrodes 22 are configured to be coupled to a controller 24. Controller 24 receives and processes the potentials recorded by the mapping electrodes 22 on expandable mapping assembly 20 and produces an electropotential map 27, also called a map, of the myoelectric and neuroelectric activity in sphincter 16. Controller 24 and electropotential map 27 are used by the physician to diagnose abnormalities and pathologies within sphincter 16 and adjoining structures which will be further discussed herein. Controller 24 can be coupled to an output or display device 29 that can include a cathode ray tube, liquid crystal display, passive or active matrix flat screen display or printer and the like.

Expandable mapping assembly 20 has a central longitudinal axis 28 and is moveable between contracted and expanded positions substantially there along. This can be accomplished by a ratchet mechanism as is known

to those skilled in the art and by the use of other mechanisms disclosed herein. The expandable mapping assembly 20 is further configured to be positionable in a sphincter 16 such as the LES or adjacent anatomical structure, such as the cardia of the stomach. Once positioned within the desired sphincter 16, the operating physician causes expandable mapping assembly 20 to expand to an expanded stationary position within the sphincter so that mapping electrodes 22 thereof engage sphincter wall 26 for sensing and detecting electrical energy or impulses therefrom. At least portions of sphincter mapping and treatment apparatus 10 may be sufficiently radiopaque in order to be visible under fluoroscopy and/or sufficiently echogenic to be visible under ultrasonography. Also, as will be discussed herein, sphincter mapping and treatment apparatus 10 can include visualization capability including, but not limited to, a viewing scope, an expanded eyepiece, fiber optics, video imaging and the like.

Referring to FIG. 2, shaft 18 is configured to be coupled to expandable mapping assembly 20 and has sufficient length to position expandable mapping assembly 20 in the LES and/or stomach using a transoral approach. Typical lengths for shaft 18 include, but are not limited to, a range of 40-180 cm. In various embodiments, shaft 18 is flexible, articulated and steerable and can contain fiber optics (including illumination and imaging fibers), fluid and gas paths, and sensor and electronic cabling. In one embodiment, shaft 18 can be a multi-lumen catheter, as is well known to those skilled in the art.

In another embodiment of the invention, an introducing member 21, also called an introducer, is used to introduce sphincter mapping and treatment apparatus 10 into the LES. Introducer 21 can also function as a sheath for expandable mapping assembly 20 to keep it in a nondeployed or

contracted state during introduction into the LES. In various embodiments, introducer 21 is flexible, articulated and steerable, and contains a continuous lumen of sufficient diameter to allow the advancement of sphincter mapping and treatment apparatus 10 within. Typical diameters for introducer 21 include 0.1 to 2 inches, while typical length include 40-180 cm. Suitable materials for introducer 21 include wire-reinforced plastic tubing as is well known to those skilled in the art.

Referring now to FIG. 3, the flexible elongate shaft 18 is circular in cross section and has proximal and distal extremities (also called ends) 30 and 32. Shaft 18 may also be coupled at its proximal end 32 to a proximal fitting 34, also called a handle, used by the physician to manipulate sphincter mapping and treatment apparatus 10 to reach treatment site 12. Shaft 18 may have one or more shaft lumens 36, that extend the full length of shaft 18, or part way from shaft proximal end 30 to shaft distal end 32. Shaft lumens 36 may be used as paths for catheters, guide wires, pull wires, insulated wires and cabling, fluid and optical fibers. Shaft lumens 36 are connected to and/or accessed by connections 38, also called connector 38, on or adjacent to proximal fitting 34. Connections 38 can include luer-lock, swage and other mechanical varieties well known to those skilled in the art. Connections 38 can also include electrical connections 38' which can include lemo connectors, micro connectors and other electrical varieties well known to those skilled in the art. Additionally, connectors 38 can include opto-electronic connections 38" which allow optical and electronic coupling of optical fibers and/or viewing scopes to illuminating sources, eye pieces and video monitors. In various embodiments, shaft 18 may stop at the proximal extremity 40 of expandable mapping assembly 20 or extend to, or past, the distal extremity 42 of expandable mapping assembly 20. Suitable materials

for shaft 18 include, but are not limited to, polyethylenes, polyurethanes and other medical plastics known to those skilled in the art.

Referring now to FIG. 4, in one embodiment of the present invention, expandable mapping assembly 20 comprises one or more elongated arms 44 that are joined at their proximal arm ends 46 and distal arm ends 48 to form a basket assembly 50. Proximal arm end 46 is attached to a supporting structure, which can be the distal end 32 of shaft 18 or a proximal cap 51. Likewise, distal arm end 48 is also attached to a supporting structure which can be a distal basket cap 52 or shaft 18. Attached arms 44 may form a variety of geometric shapes including, but not limited to, curved, rectangular, trapezoidal and triangular. Arms 44 can have a variety of cross sectional geometries including, but not limited to, circular, rectangular and crescent-shaped. Also, arms 44 are of a sufficient number (two or more), and have sufficient spring force (0.01 to 0.5 lbs. force) so as to collectively exert adequate force on sphincter wall 26 to sufficiently open and efface the folds of sphincter 16 to allow treatment with sphincter mapping and treatment apparatus 10, while preventing herniation of sphincter wall 26 into the spaces 53 between arms 44. Suitable materials for arms 44 include, but are not limited to, spring steel, stainless steel, superelastic shape memory metals such as nitinol or wire-reinforced plastic tubing as is well known to those skilled in the art.

Referring now to FIG. 4B, a plurality of spaced apart mapping electrodes 22 are carried by each arm 44 for engaging sphincter wall 26 and are electrically coupled by a conductor 23 to a multiplexer chip 25 for transmitting signals sensed thereby to controller 24 via electrical connections 38'. Various geometric patterns for placement of mapping electrodes 22 on basket assembly 50 or expandable mapping assembly 20 are disclosed later

herein. Multiplexor chip 25 transmits only a selected one of the electrode signals at a time to the controller 24, subject to switching signals that controller 24 generates. The switching signals of controller 24 serve to multiplex the electrode signals through electrical connector 38'. This reduces the number of electrical pathways required through shaft lumen 36. In various embodiments, conductor 23 can be an insulated lead wire as is well known to those skilled in the art.

In various embodiments, expandable mapping assembly 20 or basket assembly 50 may also be coupled to one or more energy delivery devices 88, also called electrodes, coupled to power source 56. Energy delivery devices 88 are used to delivery energy to treatment site 12 to produce lesions 14. Expandable mapping assembly 20 is further configured to facilitate the positioning of energy delivery devices 88, to a selectable depth in a sphincter wall 26 or adjoining anatomical structure. In one embodiment mapping electrodes 22 can also be used as energy delivery devices.

Referring to FIG. 5A, arms 44 can have an outwardly bowed shaped memory for expanding the basket assembly into engagement with sphincter wall 26 with the amount of bowing, or camber 54 being selectable from a range 0 to 2 inches from longitudinal axis 28 of basket assembly 50. For the case of a curve-shaped arm 44', expanded arms 44' are circumferentially and symmetrically spaced-apart.

In another embodiment shown in FIG 5B, an expansion device 55, which can be a balloon, is coupled to an interior or exterior of basket assembly 50. Balloon 55 is also coupled to and inflated by shaft lumen 36 using gas or liquid. In various other embodiments (not shown), arms 44 may be asymmetrically spaced and/or distributed on an arc less than 360°. Also,

arms 44 may be preshaped at time of manufacture or shaped by the physician.

Referring now to FIG. 6A, arms 44 may also be solid or hollow with a continuous lumen 58 that may be coupled with shaft lumens 36. These coupled lumens provide a path for the delivery of a fluid or electrode delivery member 60 from shaft 18 to any point on expandable mapping assembly 20. In various embodiments electrode delivery member 60 can be an insulated wire, an insulated guide wire, a plastic-coated stainless steel hypotube with internal wiring or a plastic catheter with internal wiring, all of which are known to those skilled in the art. As shown in FIG. 6B, arms 44 may also have a partially open channel 62, also called a track 62, that functions as a guide track for electrode delivery member 60. Referring back to FIG. 6A, arms 44 may have one or more apertures 64 at any point along their length that permit the controlled placement of electrodes 88 at or into sphincter wall 26. Referring now to FIG. 7, apertures 64 may have stepped sections 66 or tapered sections 68 in all or part of their length, that are used to control the penetration depth of electrodes 88 into sphincter wall 26. Referring back to FIG. 6A, apertures 64 in combination with arm lumens 58 and shaft lumens 36 may be used for the delivery of cooling solution 70 or electrolytic solution 72 to treatment site 12 as described herein. Additionally, arms 44 can also carry a plurality of longitudinally or radially spaced apart radiopaque and or echogenic markers or traces, not shown in the drawings, formed of suitable materials to permit viewing of basket assembly 50 via fluoroscopy or ultrasonography. Suitable radiopaque materials include platinum or gold, while suitable echogenic materials include gas filled micro-particles as described in US Patent No 's 5,688,490 and 5,205,287. Arms 44 may also be color-coded to facilitate their identification

via visual medical imaging methods and equipment, such as endoscopic methods, which are well known to those skilled in the art.

In another embodiment of the present invention, a radial supporting member 74 is attached to two or more arms 44. Radial supporting member 74, also called a strut, can be attached to arms 44 along a circumference of basket assembly 50 as shown in FIG. 8. Apertures 64 can extend through radial supporting member 74 in one or more places. Radial supporting member 74 serves the following functions: i) facilitates opening and effacement of the folds of sphincter 16, ii) enhances contact of apertures 64 with sphincter wall 26; and, iii) reduces or prevents the tendency of arms 44 to bunch up. The cross sectional geometry of radial supporting member 74 can be rectangular or circular, though it will be appreciated that other geometries are equally suitable.

In one embodiment shown in FIG. 9, arms 44 are attached to distal basket cap 52 that in turn, moves freely over shaft 18, but is stopped distally by shaft cap 78. One or more pull wires 80 are attached to distal basket cap 52 and also to a movable fitting 82 in proximal fitting 34 of sphincter mapping and treatment apparatus 10. When pull wire 80 is pulled back by movable fitting 82, the camber 54 of basket assembly 50 increases to 54', increasing the force and the amount of contact applied by basket assembly 50 to sphincter wall 26 or an adjoining structure. Basket assembly 50 can also be deflected from side to side using deflection mechanism 84. This allows the physician to remotely point and steer the basket assembly within the body. In one embodiment shown in FIG. 10, deflection mechanism 84 includes a second pull wire 80' attached to shaft cap 78 and also to a movable slide 86 integral to proximal fitting 34.

Turning now to a discussion of energy delivery, suitable power sources 56 and electrodes 88 that can be employed in one or more embodiments of the invention include: (i) a radio-frequency (RF) source coupled to an RF electrode, (ii) a coherent source of light coupled to an optical fiber, (iii) an incoherent light source coupled to an optical fiber, (iv) a heated fluid coupled to a catheter with a closed channel configured to receive the heated fluid, (v) a heated fluid coupled to a catheter with an open channel configured to receive the heated fluid, (vi) a cooled fluid coupled to a catheter with a closed channel configured to receive the cooled fluid, (vii) a cooled fluid coupled to a catheter with an open channel configured to receive the cooled fluid, (viii) a cryogenic fluid, (ix) a resistive heating source, (x) a microwave source providing energy from 915 MHz to 2.45 GHz and coupled to a microwave antenna, (xi) an ultrasound power source coupled to an ultrasound emitter, wherein the ultrasound power source produces energy in the range of 300 KHZ to 3 GHz, or (xii) a microwave source. For ease of discussion for the remainder of this application, the power source utilized is an RF source and electrode 88 is one or more RF electrodes 88. However, all of the other herein mentioned power sources and mapping electrodes are equally applicable to sphincter mapping and treatment apparatus 10.

For the case of RF energy, RF electrode 88 may operated in either bipolar or monopolar mode with a ground pad electrode. In a monopolar mode of delivering RF energy, a single electrode 88 is used in combination with an indifferent electrode patch that is applied to the body to form the other electrical contact and complete an electrical circuit. Bipolar operation is possible when two or more RF electrodes 88 are used. Multiple RF electrodes 88 may be used. These electrodes may be cooled as described herein. RF electrodes 88 can be attached to electrode delivery member 60 by

the use of soldering methods which are well known to those skilled in the art. Suitable solders include Megabond Solder supplied by the Megatrade Corporation (Milwaukee, Wisconsin).

Suitable electrolytic solutions 72 include saline, solutions of calcium salts, potassium salts, and the like. Electrolytic solutions 72 enhance the electrical conductivity of the targeted tissue at the treatment site 12. When a highly conductive fluid such as electrolytic solution 72 is infused into tissue the electrical resistance of the infused tissue is reduced, in turn, increasing the electrical conductivity of the infused tissue. As a result, there will be little tendency for tissue surrounding electrode 88 to desiccate (a condition described herein that increases the electrical resistance of tissue) resulting in a large increase in the capacity of the tissue to carry RF energy. Referring to FIG. 11, a zone of tissue which has been heavily infused with a concentrated electrolytic solution 72 can become so conductive as to actually act as an enhanced electrode 88'. The effect of enhanced electrode 88' is to increase the amount of current that can be conducted to the treatment site 12, making it possible to heat a much greater volume of tissue in a given time period.

Also when the power source is RF, power source 56, which will now be referred to as RF power source 56, may have multiple channels, delivering separately modulated power to each electrode 88. This reduces preferential heating that occurs when more energy is delivered to a zone of greater conductivity and less heating occurs around RF electrodes 88 which are placed into less conductive tissue. If the level of tissue hydration or the blood infusion rate in the tissue is uniform, a single channel RF power source 56 may be used to provide power for generation of lesions 14 relatively uniform in size.

RF electrodes 88 can have a variety of shapes and sizes. Possible shapes include, but are not limited to, circular, rectangular, conical and pyramidal. Electrode surfaces can be smooth or textured and concave or convex. The conductive surface area of electrode 88 can range from 0.1 mm² to 100 cm². It will be appreciated that other geometries and surface areas may be equally suitable.

In one embodiment, RF electrodes 88 can be in the shape of needles and of sufficient sharpness and length to penetrate into the smooth muscle of the esophageal wall, sphincter 16 or other anatomical structure. In this embodiment shown in FIG.s 12 and 13, needle electrodes 90 are attached to arms 44 and have an insulating layer 92, covering an insulated segment 94 except for an exposed segment 95. For purposes of this disclosure, an insulator or insulation layer is a barrier to either thermal, RF or electrical energy flow. Insulated segment 94 is of sufficient length to extend into sphincter wall 26 and minimize the transmission of RF energy to a protected site 97 near or adjacent to insulated segment 94 (see FIG. 13). Typical lengths for insulated segment 94 include, but are not limited to, 1-4 mm. Suitable materials for needle electrodes 90 include, but are not limited to, 304 stainless steel and other stainless steels known to those skilled in the art. Suitable materials for insulating layer 92 include, but are not limited to, polyimides and polyamides.

During introduction of sphincter mapping and treatment apparatus 10, basket assembly 50 is in a contracted state. Once sphincter mapping and treatment apparatus 10 is properly positioned at the treatment site 12, needle electrodes 90 are deployed by expansion of basket assembly 50, resulting in the protrusion of needle electrodes 90 into the smooth muscle tissue of sphincter wall 26 (refer to FIG. 14). The depth of needle penetration is

selectable from a range of 0.5 to 5 mm and is accomplished by indexing movable fitting 82 so as to change the camber 54 of arm 44 in fixed increments that can be selectable in a range from 0.1 to 4 mms. Needle electrodes 90 are coupled to power source 56 via insulated wire 60.

5 In another embodiment of sphincter mapping and treatment apparatus 10 shown in FIG. 15, needle electrodes 90 are advanced out of apertures 64 in basket arms 44 into the smooth muscle of the esophageal wall or other sphincter 16. In this case, needle electrodes 90 are electrically coupled to RF power source 56 by electrode delivery member 60. In this embodiment, the
10 depth of needle penetration is selectable via means of stepped sections 66 or tapered sections 68 located in apertures 64. Referring to FIG. 16, apertures 64 and needle electrodes 90 are configured such that the penetration angle 96 (also called an emergence angle 96) of needle electrode 90 into sphincter wall 26 remains sufficiently constant during the time needle electrode 90 is
15 being inserted into sphincter wall 26, such that there is no tearing or unnecessary trauma to sphincter wall tissue. This is facilitated by the selection of the following parameters and criteria: i) the emergence angle 96 of apertures 64 which can vary from 1 to 90°, ii) the arc radius 98 of the curved section 100 of aperture 64 which can vary from 0.001 to 2 inch, iii)
20 the amount of clearance between the aperture inner diameter 102 and the needle electrode outside diameter 103 which can vary between 0.001" and 0.1"; and, iv) use of a lubricous coating on electrode delivery member 60 such as a Teflon ® or other coatings well known to those skilled in the art. Also in this embodiment, insulated segment 94 can be in the form of an
25 sleeve that may be adjustably positioned at the exterior of needle electrode 90.

In another alternative embodiment shown in FIG. 17, electrode delivery member 60 with attached needle electrodes 90, can exit from shaft lumen 36 at distal shaft end 32 and be positioned into contact with sphincter wall 26. This process may be facilitated by use of a hollow guiding member 101, known to those skilled in the art as a guiding catheter, through which electrode delivery member 60 is advanced. Guiding catheter 101 may also include stepped sections 66 or tapered sections 68 at it distal end to control the depth of penetration of needle electrode 90 into sphincter wall 26.

RF energy flowing through tissue causes heating of the tissue due to absorption of the RF energy by the tissue and ohmic heating due to electrical resistance of the tissue. This heating can cause injury to the affected cells and can be substantial enough to cause cell death, a phenomenon also known as cell necrosis. For ease of discussion for the remainder of this application, cell injury will include all cellular effects resulting from the delivery of energy from electrode 88 up to, and including, cell necrosis. Cell injury can be accomplished as a relatively simple medical procedure with local anesthesia. In one embodiment, cell injury proceeds to a depth of approximately 1-4 mm from the surface of the mucosal layer of sphincter 16 or that of an adjoining anatomical structure.

Referring now to FIGS 18A, 18B, 18C and 18D, mapping electrodes 22, RF electrodes 88 and/or apertures 64 may be distributed in a variety of patterns along expandable mapping assembly 20 or basket assembly 50 to facilitate mapping and in order to produce a desired placement and pattern of lesions 14. Typical electrode (both mapping and RF varieties) and aperture distribution patterns include, but are not limited to, a radial distribution 104 (refer to FIG. 18A), a longitudinal distribution 105 (refer to FIG. 18B), a spiral distribution 106 (refer to FIG. 18C) and a combination of longitudinal

and radial distributions 107 (refer to FIG. 18D). It will be appreciated that other combinations, patterns and geometries for electrode and aperture placement, may also be suitable. These electrodes may be cooled as described hereafter.

5 FIG. 19 is a flow chart illustrating one embodiment of the procedure for using sphincter mapping and treatment apparatus 10. In this embodiment, sphincter mapping and treatment apparatus 10 is first introduced into the esophagus under local anesthesia. Sphincter mapping and treatment apparatus 10 can be introduced into the esophagus by itself or
10 through a lumen in an endoscope (not shown), such as disclosed in U.S. Patents Nos. 5,448,990 and 5,275,608, incorporated herein by reference, or similar esophageal access device known to those skilled in the art. Basket assembly 50 is expanded as described herein. This serves to temporarily dilate the LES or sufficiently to efface a portion of or all of the folds of the
15 LES. In an alternative embodiment, esophageal dilation and subsequent LES fold effacement can be accomplished by insufflation of the esophagus (a known technique) using gas introduced into the esophagus through shaft lumen 36, or an endoscope or similar esophageal access device as described above. Once treatment is completed, basket assembly 50 is returned to its
20 predeployed or contracted state and sphincter mapping and treatment apparatus 10 is withdrawn from the esophagus. This results in the LES returning to approximately its pretreatment state and diameter. It will be appreciated that the above procedure is applicable in whole or part to the treatment of other sphincters in the body.

25 As discussed previously, controller 24 and electropotential map 27 are used to by the physician to diagnose abnormalities and pathologies within sphincter 16 and adjoining structures. More specifically, they are used to

identify electrical events that include depolarization, contraction and repolarization. This information is used by the physician to determine target treatment sites 12 in the LES or adjoining anatomical structures that are acting as foci 108 or pathways 109 for aberrant electrical signals 111 causing abnormal or otherwise inappropriate relaxation of the smooth muscle of the LES or other sphincter 16 (Refer to FIG. 20). These targeted treatment sites 12 are then treated as described herein so as to create lesions 14 which disrupt, block or otherwise prevent the generation and transmission of sufficient aberrant electrical signals 111 to cause relaxation of the LES or other sphincter wall 26.

A variety of other diagnostic methods can be employed as an adjunct to surface mapping of sphincter wall 26. These method include, but are not limited to, the following: (i) visualization of the interior surface of the esophagus via an endoscope or other viewing apparatus inserted into the esophagus, (ii) visualization of the interior morphology of the esophageal wall using ultrasonography to establish a baseline for the tissue to be treated; and, (iii) impedance measurement to determine the electrical conductivity between the esophageal mucosal layers and sphincter mapping and treatment apparatus 10.

In the treatment phase of the procedure, the delivery of energy to treatment site 12 can be conducted under feedback control, manually or by a combination of both. Feedback control (described herein) enables sphincter mapping and treatment apparatus 10 to be positioned and retained in the esophagus during treatment with minimal attention by the physician. RF electrodes 88 can be multiplexed in order to treat the entire targeted treatment site 12 or only a portion thereof. Feedback can be included and is achieved by the use of one or more of the following methods: (i)

visualization, (ii) impedance measurement, (iii) ultrasonography, (iv) temperature measurement; and, (v) sphincter contractile force measurement via manometry. The feedback mechanism permits the selected on-off switching of different RF electrodes 88 in a desired pattern, which can be sequential from one electrode 88 to an adjacent electrode 88, or can jump around between non-adjacent RF electrodes 88. Individual RF electrodes 88 are multiplexed and volumetrically controlled by controller 23'.

The area and magnitude of cell injury in the LES or sphincter 16 can vary. However, it is desirable to deliver sufficient energy to the targeted treatment site 12 to be able to achieve tissue temperatures in the range of 55-95° C and produce lesions 14 at depths ranging from 1-4 mm from the interior surface of the LES or sphincter wall 26. Typical energies delivered to the esophageal wall include, but are not limited to, a range between 100 and 50,000 joules per electrode 88. It is also desirable to deliver sufficient energy such that the resulting lesions 14 have a sufficient magnitude and area of cell injury to cause an infiltration of lesion 14 by fibroblasts 110, myofibroblasts 112, macrophages 114 and other cells involved in the tissue healing process (refer to FIG. 21). As shown in FIG. 22, these cells cause a contraction of tissue around lesion 14, decreasing its volume and, or altering the biomechanical properties at lesion 14 so as to result in a tightening of LES or sphincter 16. These changes are reflected in transformed lesion 14' shown in FIG. 19B. The diameter of lesions 14 can vary between 0.1 to 4 mm. It is preferable that lesions 14 are less than 4 mm in diameter in order to reduce the risk of thermal damage to the mucosal layer. In one embodiment, a 2 mm diameter lesion 14 centered in the wall of the smooth muscle provides a 1 mm buffer zone to prevent damage to the mucosa, submucosa and adventitia, while still allowing for cell infiltration and

subsequent sphincter tightening on approximately 50% of the thickness of the wall of the smooth muscle (refer to FIG. 23).

From a diagnostic standpoint, it is desirable to image the interior surface and wall of the LES or other sphincter 16, including the size and position of created lesions 14. It is desirable to create a map of these structures which can be inputted to controller 23' and used to direct the delivery of energy to treatment site 12. Referring to FIG. 24, this can be accomplished through the use of ultrasonography (a known procedure) which involves the use of an ultrasound power source 116 coupled to one or more ultrasound transducers 118 that are positioned on expandable mapping assembly 20 or basket assembly 50. An output is associated with ultrasound power source 116.

Each ultrasound transducer 118 can include a piezoelectric crystal 120 mounted on a backing material 122 that is in turn, attached to expandable mapping assembly 20 or basket assembly 50. An ultrasound lens 124, fabricated on an electrically insulating material 126, is mounted over piezoelectric crystal 120. Piezoelectric crystal 120 is connected by electrical leads 128 to ultrasound power source 116. Each ultrasound transducer 118 transmits ultrasound energy into adjacent tissue. Ultrasound transducers 118 can be in the form of an imaging probe such as Model 21362, manufactured and sold by Hewlett Packard Company, Palo Alto, California. In one embodiment, two ultrasound transducers 118 are positioned on opposite sides of expandable mapping assembly 20 or basket assembly 50 to create an image depicting the size and position of lesion 14 in selected sphincter 16.

It is desirable that lesions 14 are predominantly located in the smooth muscle layer of selected sphincter 16 at the depths ranging from 1 to 4 mm from the interior surface of sphincter wall 26. However, lesions 14 can vary

both in number and position within sphincter wall 26. It may be desirable to produce a pattern of multiple lesions 14 within the sphincter smooth muscle tissue in order to obtain a selected degree of tightening of the LES or other sphincter 16. Typical lesion patterns shown in FIGS 25A-D include, but are not limited to, (i) a concentric circle of lesions 14 all at fixed depth in the smooth muscle layer evenly spaced along the radial axis of sphincter 16, (ii) a wavy or folded circle of lesions 14 at varying depths in the smooth muscle layer evenly spaced along the radial axis of sphincter 16, (iii) lesions 14 randomly distributed at varying depths in the smooth muscle, but evenly spaced in a radial direction; and, (iv) an eccentric pattern of lesions 14 in one or more radial locations in the smooth muscle wall. Accordingly, the depth of RF and thermal energy penetration sphincter 16 is controlled and selectable. The selective application of energy to sphincter 16 may be the even penetration of RF energy to the entire targeted treatment site 12, a portion of it, or applying different amounts of RF energy to different sites depending on the condition of sphincter 16. If desired, the area of cell injury can be substantially the same for every treatment event.

Referring to FIG. 26, it may be desirable to cool all or a portion of the area near the electrode-tissue interface 130 before, during or after the delivery of energy in order to reduce the degree and area of cell injury. Specifically, the use of cooling preserves the mucosal layers of sphincter wall 26 and protects, or otherwise reduces the degree of cell damage to cooled zone 132 in the vicinity of lesion 14. Referring now to FIG. 27, this can be accomplished through the use of cooling solution 70 that is delivered by apertures 64 which is in fluid communication with shaft lumen 36 that is, in turn, in fluid communication with fluid reservoir 134 and a control unit 136, whose operation is described herein, that controls the delivery of the fluid.

Similarly, it may also be desirable to cool all or a portion of the electrode 88. The rapid delivery of heat through electrode 88, may result in the build up of charred biological matter on electrode 88 (from contact with tissue and fluids e.g., blood) that impedes the flow of both thermal and electrical energy from electrode 88 to adjacent tissue and causes an electrical impedance rise beyond a cutoff value set on RF power source 56. A similar situation may result from the desiccation of tissue adjacent to electrode 88. Cooling of the electrode 88 can be accomplished by cooling solution 70 that is delivered by apertures 64 as described previously. Referring now to FIG. 28, electrode 88 may also be cooled via a fluid channel 138 in electrode 88 that is in fluid communication with fluid reservoir 134 and control unit 136.

As shown in FIG. 29, one or more sensors 140 may be positioned adjacent to or on electrode 88 for sensing the temperature of sphincter tissue at treatment site 12. More specifically, sensors 140 permit accurate determination of the surface temperature of sphincter wall 26 at electrode-tissue interface 130. This information can be used to regulate both the delivery of energy and cooling solution 70 to the interior surface of sphincter wall 26. In various embodiments, sensors 140 can be positioned at any position on expandable mapping assembly 20 or basket assembly 50. Suitable sensors that may be used for sensor 140 include: thermocouples, fiber optics, resistive wires, thermocouple IR detectors, and the like. Suitable thermocouples for sensor 140 include: T type with copper constantene, J type, E type and K types as are well known those skilled in the art.

Temperature data from sensors 140 are fed back to control unit 136 and through an algorithm which is stored within a microprocessor memory of control unit 136. Instructions are sent to an electronically controlled

micropump (not shown) to deliver fluid through the fluid lines at the appropriate flow rate and duration to provide control temperature at the electrode-tissue interface 130 (refer to FIG. 27).

5 The reservoir of control unit 136 may have the ability to control the temperature of the cooling solution 70 by either cooling the fluid or heating the fluid. Alternatively, a fluid reservoir 134 of sufficient size may be used in which the cooling solution 70 is introduced at a temperature at or near that of the normal body temperature. Using a thermally insulated reservoir 142, adequate control of the tissue temperature may be accomplished without
10 need of refrigeration or heating of the cooling solution 70. Cooling solution 70 flow is controlled by control unit 136 or another feedback control system (described herein) to provide temperature control at the electrode-tissue interface 130.

15 A second diagnostic phase may be included after the treatment is completed. This provides an indication of LES tightening treatment success, and whether or not a second phase of treatment, to all or only a portion of the esophagus, now or at some later time, should be conducted. The second diagnostic phase is accomplished through one or more of the following methods: (i) visualization, (ii) measuring impedance, (iii) ultrasonography,
20 (iv) temperature measurement, or (v) measurement of LES tension and contractile force via manometry.

In one embodiment, sphincter mapping and treatment apparatus 10 is coupled to an open or closed loop feedback system. Referring now to FIG. 30, an open or closed loop feedback system couples sensor 346 to energy
25 source 392. In this embodiment, electrode 314 is one or more RF electrodes 314.

The temperature of the tissue, or of RF electrode 314 is monitored, and the output power of energy source 392 adjusted accordingly. The physician can, if desired, override the closed or open loop system. A microprocessor 394 can be included and incorporated in the closed or open loop system to switch power on and off, as well as modulate the power. The closed loop system utilizes microprocessor 394 to serve as a controller, monitor the temperature, adjust the RF power, analyze the result, refeed the result, and then modulate the power.

With the use of sensor 346 and the feedback control system a tissue adjacent to RF electrode 314 can be maintained at a desired temperature for a selected period of time without causing a shut down of the power circuit to electrode 314 due to the development of excessive electrical impedance at electrode 314 or adjacent tissue as is discussed herein. Each RF electrode 314 is connected to resources which generate an independent output. The output maintains a selected energy at RF electrode 314 for a selected length of time.

Current delivered through RF electrode 314 is measured by current sensor 396. Voltage is measured by voltage sensor 398. Impedance and power are then calculated at power and impedance calculation device 400. These values can then be displayed at user interface and display 402. Signals representative of power and impedance values are received by a controller 404.

A control signal is generated by controller 404 that is proportional to the difference between an actual measured value, and a desired value. The control signal is used by power circuits 406 to adjust the power output in an appropriate amount in order to maintain the desired power delivered at respective RF electrodes 314.

In a similar manner, temperatures detected at sensor 346 provide feedback for maintaining a selected power. Temperature at sensor 346 is used as a safety means to interrupt the delivery of energy when maximum pre-set temperatures are exceeded. The actual temperatures are measured at temperature measurement device 408, and the temperatures are displayed at user interface and display 402. A control signal is generated by controller 404 that is proportional to the difference between an actual measured temperature and a desired temperature. The control signal is used by power circuits 406 to adjust the power output in an appropriate amount in order to maintain the desired temperature delivered at the sensor 346. A multiplexer can be included to measure current, voltage and temperature, at the sensor 346, and energy can be delivered to RF electrode 314 in monopolar or bipolar fashion.

Controller 404 can be a digital or analog controller, or a computer with software. When controller 404 is a computer it can include a CPU coupled through a system bus. This system can include a keyboard, a disk drive, or other non-volatile memory systems, a display, and other peripherals, as are known in the art. Also coupled to the bus is a program memory and a data memory.

User interface and display 402 includes operator controls and a display. Controller 404 can be coupled to imaging systems including, but not limited to, ultrasound, CT scanners, X-ray, MRI, mammographic X-ray and the like. Further, direct visualization and tactile imaging can be utilized.

The output of current sensor 396 and voltage sensor 398 are used by controller 404 to maintain a selected power level at RF electrode 314. The amount of RF energy delivered controls the amount of power. A profile of

the power delivered to electrode 314 can be incorporated in controller 404 and a preset amount of energy to be delivered may also be profiled.

Circuitry, software and feedback to controller 404 result in process control, the maintenance of the selected power setting which is independent of changes in voltage or current, and is used to change the following process variables: (i) the selected power setting, (ii) the duty cycle (e.g., on-off time), (iii) bipolar or monopolar energy delivery; and, (iv) fluid delivery, including flow rate and pressure. These process variables are controlled and varied, while maintaining the desired delivery of power independent of changes in voltage or current, based on temperatures monitored at sensor 346.

Referring now to FIG. 31, current sensor 396 and voltage sensor 398 are connected to the input of an analog amplifier 410. Analog amplifier 410 can be a conventional differential amplifier circuit for use with sensor 346. The output of analog amplifier 410 is sequentially connected by an analog multiplexer 412 to the input of A/D converter 414. The output of analog amplifier 410 is a voltage which represents the respective sensed temperatures. Digitized amplifier output voltages are supplied by A/D converter 414 to microprocessor 394. Microprocessor 394 may be a type 68HCII available from Motorola. However, it will be appreciated that any suitable microprocessor or general purpose digital or analog computer can be used to calculate impedance or temperature.

Microprocessor 394 sequentially receives and stores digital representations of impedance and temperature. Each digital value received by microprocessor 394 corresponds to different temperatures and impedances.

Calculated power and impedance values can be indicated on user interface and display 402. Alternatively, or in addition to the numerical

indication of power or impedance, calculated impedance and power values can be compared by microprocessor 394 to power and impedance limits. When the values exceed predetermined power or impedance values, a warning can be given on user interface and display 402, and additionally, the delivery of RF energy can be reduced, modified or interrupted. A control signal from microprocessor 394 can modify the power level supplied by energy source 392.

FIG. 32 illustrates a block diagram of a temperature and impedance feedback system that can be used to control the delivery of energy to tissue site 416 by energy source 392 and the delivery of cooling solution 70 to electrode 314 and/or tissue site 416 by flow regulator 418. Energy is delivered to RF electrode 314 by energy source 392, and applied to tissue site 416. A monitor 420 ascertains tissue impedance, based on the energy delivered to tissue, and compares the measured impedance value to a set value. If the measured impedance exceeds the set value, a disabling signal 422 is transmitted to energy source 392, ceasing further delivery of energy to RF electrode 314. If measured impedance is within acceptable limits, energy continues to be applied to the tissue.

The control of cooling solution 70 to electrode 314 and/or tissue site 416 is done in the following manner. During the application of energy, temperature measurement device 408 measures the temperature of tissue site 416 and/or RF electrode 314. A comparator 424 receives a signal representative of the measured temperature and compares this value to a pre-set signal representative of the desired temperature. If the tissue temperature is too high, comparator 424 sends a signal to a flow regulator 418 (connected to an electronically controlled micropump, not shown) representing a need for an increased cooling solution flow rate. If the

measured temperature has not exceeded the desired temperature, comparator 424 sends a signal to flow regulator 418 to maintain the cooling solution flow rate at its existing level.

5 The foregoing description of a preferred embodiment of the invention has been presented for purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise forms disclosed. Obviously, many modifications and variations will be apparent to practitioners skilled in this art. It is intended that the scope of the invention be defined by the following claims and their equivalents.

10 What is claimed is:

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213